


RightWave® EDF MP980 Optical Fiber

P/N: 27299



Overview

The RightWave EDF portfolio has a broad EDF product line with each fiber type optimized for different applications.

RightWave EDF MP980 is a medium power fiber designed for many configurations of EDFAs. It can be used as a single-stage amplifier fiber at higher than 100mW pump powers. The most popular fiber type used in EDFA design, due to a well-balanced combination of broadband gain, gain flatness, bend loss and noise figure.

Typical Applications

CATV Amplifiers

DWDM Amplifiers

Single-Stage Amplifiers at
Very High Pump Powers in
Excess of 200 mW



A Furukawa Company

RightWave® EDF MP980 Optical Fiber

P/N: 27299

| Product Specifications | |
|-----------------------------------|-----------------------------------|
| Product Description | RightWave EDF MP980 Optical Fiber |
| Optical Characteristics | |
| Peak Absorption @ 1530 nm | 6.5 ± 1.0 dB/m |
| Cutoff Wavelength | 860 - 950 nm |
| Mode Field Diameter @ 1550 nm | 6.2 ± 0.7 μm |
| Numerical Aperture | 0.21 ± 0.02 |
| PMD (Typical) | ≤ 2 fs/m |
| Loss @ 1200 nm | < 5 dB/km |
| Physical Characteristics | |
| Cladding Mean Diameter | 125 μm |
| Core/Cladding Concentricity Error | ≤ 0.3 μm |
| Coating Diameter | 245 μm |
| Mechanical and Environmental | |
| Proof Test Level | 1.38 GPa (200 kpsi) |
| Order by Part Number | 27299 |

OPTIONS: Coils or Spools, Color-Coded Buffers, Custom Designs, Fibers Available in Long Lengths on Standard Spools, Fibers Available in Predetermined Lengths and Coiled to Given Diameters, Fibers Available with Natural or Colored Buffer, Fibers May be Customized to Suit Your Specific Application

NOTE: Compatible with OASiX® Software Package: Accurate prediction of EDF performance is essential to applications design. OFS offers specialized OASiX Amplifier Simulation System Software, which allows the designer to predict EDFA performance at all pump powers for the specific lot of EDF purchased. OASiX is also available in a DLL version for compatibility with external optimization tools.

For additional information please contact your sales representative.

You can also visit our website at www.ofsoptics.com or call 1-888-fiberhelp (1-888-342-3743) USA or 1-770-798-5555 outside the USA.



Copyright © 2023 OFS Fitel, LLC.
All rights reserved, printed in USA.

OFS Marketing Communications
Date: 02/23

For a full list of our certifications, visit our website.



RightWave and OASiX are registered trademarks of OFS Fitel, LLC. OFS reserves the right to make changes to the prices and product(s) described in this document at any time without notice. This document is for informational purposes only and is not intended to modify or supplement any OFS warranties or specifications relating to any of its products or services.